



CWENG Test Prep

Free Practice Test — 30 Real Exam-Style Questions

with full answer key & explanations

**Unlock the full bank of 505 questions
+ unlimited timed mock exams + mistake book**

Practice on the web: <https://certs.theorypractice.app/cweng>

\$2.99 / week · \$6.99 / month · cancel anytime

What you unlock: all 505 questions • unlimited timed mock exams • mistake book • instant explanations

Also on iOS & Android — and watch the full Q&A walkthrough on [YouTube @CertsQuizPrep](#)



Unlock all 505 questions + timed mock exams

→ <https://certs.theorypractice.app/cweng>

\$2.99/week or \$6.99/month · cancel anytime · scan to start



Practice Questions

Try all 30 first, then check the answer key at the back.

Want the other 475+ questions & full timed mock exams? Unlock at
<https://certs.theorypractice.app/cweng>

1. In a constant current (CC) arc welding circuit, what happens to the current when the arc length changes?

- A. The current changes directly proportional to the arc length
- B. Both current and voltage remain constant
- C. The current increases as arc length increases
- D. The current remains relatively stable while the voltage changes

2. What is the function of a rectifier in a DC arc welding power source?

- A. To stabilize voltage fluctuations
- B. To reduce current flow
- C. To convert AC to DC
- D. To convert DC to AC

3. In welding circuit analysis, what does open circuit voltage (OCV) represent?

- A. The voltage required to maintain a stable arc
- B. The voltage present when no welding arc is established
- C. The maximum voltage during welding
- D. The voltage drop across the workpiece

Also on iOS & Android — and watch the full Q&A walkthrough on [YouTube](#)
[@CertsQuizPrep](#)

4. Which of the following best describes a constant voltage (CV) arc welding circuit?

- A. The power source maintains voltage at a set point while current self-adjusts
- B. Both voltage and current remain fixed during welding
- C. The power source maintains current at a set point while voltage self-adjusts
- D. The circuit automatically increases voltage as arc length increases



Unlock all 505 questions + timed mock exams

→ <https://certs.theorypractice.app/cweng>

\$2.99/week or \$6.99/month · cancel anytime · scan to start



5. What component in an inverter welding power source allows for high-frequency operation?

- A. Capacitors
- B. Inductors
- C. Resistors
- D. Transistors

6. According to Ohm's Law, what happens to current in a welding circuit if resistance increases while voltage remains constant?

- A. Current remains the same
- B. Current fluctuates randomly
- C. Current decreases
- D. Current increases

Want the other 475+ questions & full timed mock exams? Unlock at
<https://certs.theorypractice.app/cweng>

7. Which electrical characteristic is most important to control in SMAW (Stick) welding circuits?

- A. Frequency
- B. Current (amperage)
- C. Voltage
- D. Impedance

8. In an arc welding circuit, what is the primary purpose of an inductor?

- A. To stabilize the arc by resisting rapid changes in current
- B. To increase the voltage across the arc
- C. To convert AC to DC
- D. To store electrical charge

9. What effect does increased inductance have on a GMAW (MIG) welding circuit?

- A. Increases deposition rate
- B. Decreases penetration depth
- C. Increases arc temperature
- D. Reduces spatter by smoothing current transitions

Also on iOS & Android — and watch the full Q&A walkthrough on [YouTube](#)
[@CertsQuizPrep](#)



Unlock all 505 questions + timed mock exams

→ <https://certs.theorypractice.app/cweng>

\$2.99/week or \$6.99/month · cancel anytime · scan to start



10. What is the relationship between duty cycle and current output in a welding power source?

- A. Current output has no effect on duty cycle
- B. Duty cycle only depends on voltage, not current
- C. As current output increases, duty cycle decreases
- D. As current output increases, duty cycle increases

11. In a welding circuit with DCEN (Direct Current Electrode Negative), where does the majority of heat generation occur?

- A. In the power source
- B. At the workpiece
- C. At the electrode
- D. Equally at both electrode and workpiece

12. What circuit component is primarily responsible for voltage reduction in traditional transformer-based welding power sources?

- A. Transformer
- B. Rectifier
- C. Capacitor
- D. Resistor

Want the other 475+ questions & full timed mock exams? Unlock at
<https://certs.theorypractice.app/cweng>

13. What fundamental characteristic distinguishes solid-state welding from fusion welding processes?

- A. Requires filler materials
- B. Produces a fusion zone
- C. Always requires external heat sources
- D. No melting of the base materials occurs

14. Which of the following is NOT a common type of friction welding?

- A. Inertia friction welding
- B. Friction stir welding
- C. Plasma friction welding
- D. Linear friction welding



Unlock all 505 questions + timed mock exams

→ <https://certs.theorypractice.app/cweng>

\$2.99/week or \$6.99/month · cancel anytime · scan to start



15. In ultrasonic welding, what is the primary mechanism that creates the bond between materials?

- A. Plasma arc generation at the joint
- B. High-frequency mechanical vibrations causing localized friction
- C. Electrical resistance at the interface
- D. Chemical reaction between filler materials

Also on iOS & Android — and watch the full Q&A walkthrough on [YouTube](#)
[@CertsQuizPrep](#)

16. Which surface condition is most critical for successful diffusion welding?

- A. Extremely clean surfaces free of oxides and contaminants
- B. Rough surface texture for mechanical interlocking
- C. Pre-applied flux coating
- D. Pre-heated surfaces above melting point

17. What is a key advantage of friction stir welding compared to conventional fusion welding processes?

- A. Higher heat input for thick sections
- B. Lower equipment costs
- C. Less stringent joint preparation requirements
- D. Reduced susceptibility to solidification defects

18. Which material combination is MOST suitable for diffusion bonding?

- A. Copper to ceramic
- B. Polymers to metals
- C. Titanium to titanium
- D. Aluminum to steel

Want the other 475+ questions & full timed mock exams? Unlock at
<https://certs.theorypractice.app/cweng>

19. In explosion welding, what creates the bond between the materials?

- A. Chemical reaction between flux and base metals
- B. High-velocity collision creating extreme interfacial pressure
- C. Melting and solidification of both materials
- D. Diffusion of atoms across the interface



Unlock all 505 questions + timed mock exams

→ <https://certs.theorypractice.app/cweng>

\$2.99/week or \$6.99/month · cancel anytime · scan to start



20. Which process parameter is MOST critical in conventional friction welding?

- A. Rotational speed
- B. Shield gas composition
- C. Electrode type
- D. Flux composition

21. What type of joint configuration is typically required for ultrasonic welding?

- A. Butt joint
- B. T-joint
- C. Edge joint
- D. Lap joint

Also on iOS & Android — and watch the full Q&A walkthrough on [YouTube](#)
[@CertsQuizPrep](#)

22. Which of the following is a common quality issue in friction stir welding?

- A. Porosity from gas entrapment in molten pool
- B. Undercutting from excessive arc force
- C. Tunneling defects due to insufficient heat input
- D. Centerline cracking from rapid solidification

23. What is the primary purpose of the axial force in conventional friction welding?

- A. To prevent oxidation of the weld pool
- B. To maintain pressure between components during heating and forging
- C. To control the rotation speed of the workpiece
- D. To generate electrical current at the interface

24. Which solid-state welding process is BEST suited for joining thermoplastic components in electronic assemblies?

- A. Ultrasonic welding
- B. Friction stir welding
- C. Explosion welding
- D. Diffusion bonding

Want the other 475+ questions & full timed mock exams? Unlock at
<https://certs.theorypractice.app/cweng>



Unlock all 505 questions + timed mock exams

→ <https://certs.theorypractice.app/cweng>

\$2.99/week or \$6.99/month · cancel anytime · scan to start



25. What is the primary difference between CO_2 and Nd:YAG lasers used in welding?

- A. Maximum power output
- B. Cooling requirements
- C. Pulse frequency capabilities
- D. Wavelength of the laser beam

26. Which vacuum level is typically required for electron beam welding?

- A. Atmospheric pressure
- B. 10^{-12} to 10^{-15} Torr
- C. 10^{-3} to 10^{-6} Torr
- D. 1 to 10 Torr

27. In electron beam welding, the electron beam is primarily focused by:

- A. Gas pressure differentials
- B. Electromagnetic lenses
- C. Optical lenses
- D. Mechanical apertures

Also on iOS & Android — and watch the full Q&A walkthrough on [YouTube](#)
[@CertsQuizPrep](#)

28. Which mechanism primarily creates the keyhole in high energy beam welding?

- A. Vaporization of the material at high power density
- B. Mechanical drilling action of the beam
- C. Chemical reaction between beam and material
- D. Expansion of trapped gases in the material

29. What is the typical power density range required for keyhole mode welding in laser beam processes?

- A. 10^3 W/cm²
- B. 10^{12} W/cm²
- C. 10 to 100 W/cm²
- D. 10^6 W/cm² or higher



Unlock all 505 questions + timed mock exams

→ <https://certs.theorypractice.app/cweng>

\$2.99/week or \$6.99/month · cancel anytime · scan to start



30. Which of the following materials is particularly challenging to weld with CO_2 laser due to reflectivity issues?

- A. Stainless steel
- B. Titanium
- C. Aluminum
- D. Carbon steel



Unlock all 505 questions + timed mock exams

→ <https://certs.theorypractice.app/cweng>

\$2.99/week or \$6.99/month · cancel anytime · scan to start



Answer Key & Explanations

You just practised 30 of 505. Unlock every question + timed mocks at
<https://certs.theorypractice.app/cweng>

1. D — The current remains relatively stable while the voltage changes

Constant current power sources maintain a relatively stable amperage despite changes in arc length, which causes voltage to change instead. This makes them ideal for processes where maintaining consistent amperage is critical, such as SMAW.

2. C — To convert AC to DC

Rectifiers convert alternating current (AC) to direct current (DC) by allowing current to flow in only one direction, which is essential for DC welding applications.

3. B — The voltage present when no welding arc is established

Open circuit voltage is the voltage measured across the output terminals of a welding power source when no welding is taking place (no current flowing). It must be high enough to establish an arc but not excessive for safety reasons.

4. A — The power source maintains voltage at a set point while current self-adjusts

In constant voltage circuits, the power source maintains relatively stable voltage while allowing current to vary based on the physical distance between the electrode and workpiece. This self-regulation makes them ideal for GMAW (MIG) welding.

5. D — Transistors

Transistors (specifically IGBTs or MOSFETs) in inverter welding power sources rapidly switch the current on and off at high frequencies, allowing for more efficient and compact designs compared to traditional transformer-based power sources.

6. C — Current decreases

Ohm's Law ($I = V/R$) dictates that current is inversely proportional to resistance when voltage is constant. If resistance increases, the current will decrease proportionally.

7. B — Current (amperage)

SMAW welding uses a constant current (CC) characteristic where the amperage remains relatively stable despite changes in arc length. This helps maintain a stable arc even with hand movement variations.

8. A — To stabilize the arc by resisting rapid changes in current

Inductors in welding circuits create a choke effect that helps stabilize the arc by resisting rapid changes in current, reducing spatter and improving weld quality.

9. D — Reduces spatter by smoothing current transitions

Increased inductance in GMAW circuits smooths out current fluctuations, reducing spatter by slowing the rate of current change during short circuits and arc re-ignition.

10. C — As current output increases, duty cycle decreases

Duty cycle and current output have an inverse relationship. Higher current outputs can only be sustained for



Unlock all 505 questions + timed mock exams

→ <https://certs.theorypractice.app/cweng>

\$2.99/week or \$6.99/month · cancel anytime · scan to start

Unofficial study material · not affiliated with any certifying body



shorter periods (lower duty cycle) due to heat generation in the power source components.

11. B — At the workpiece

In DCEN (also called DCSP - Direct Current Straight Polarity), electrons flow from the electrode to the workpiece, generating approximately 70% of the heat at the workpiece, which results in deeper penetration.

12. A — Transformer

In traditional welding power sources, transformers reduce the high input voltage (e.g., 230V or 460V) to the lower voltages needed for welding (typically 20-80V) through electromagnetic induction.

13. D — No melting of the base materials occurs

Solid-state welding processes join materials without melting the base materials. The joining occurs below the melting point through mechanisms like friction, pressure, or atomic diffusion at the interface, maintaining the solid state throughout the process.

14. C — Plasma friction welding

Plasma friction welding is not a standard friction welding type. The common types are conventional (direct drive) friction welding, friction stir welding, inertia friction welding, and linear friction welding.

15. B — High-frequency mechanical vibrations causing localized friction

Ultrasonic welding uses high-frequency mechanical vibrations (typically 20-40 kHz) to generate friction and localized heat at the interface between materials, creating atomic bonds without bulk melting. The oscillating shear forces break down surface oxides, allowing direct material contact.

16. A — Extremely clean surfaces free of oxides and contaminants

Diffusion welding relies on atomic migration across the interface, which requires extremely clean surfaces free of oxides, contaminants, and other impurities that would inhibit diffusion. Surface cleanliness is therefore the most critical factor for successful bonds.

17. D — Reduced susceptibility to solidification defects

Since friction stir welding operates below the melting point of the materials being joined, it avoids many of the solidification defects common to fusion welding, such as porosity, segregation, and solidification cracking.

18. C — Titanium to titanium

Titanium to titanium is ideal for diffusion bonding because titanium forms a stable oxide that can be dissolved during the diffusion bonding process, and titanium has good diffusivity at elevated temperatures below its melting point, facilitating strong atomic bonds.

19. B — High-velocity collision creating extreme interfacial pressure

Explosion welding creates a bond through extreme pressure from controlled detonation, which causes the surfaces to collide at high velocity. This produces a wavy interface with mechanical interlocking and localized melting at collision points, creating a metallurgical bond.

20. A — Rotational speed

Rotational speed directly influences the heat generation and material plasticization in conventional friction welding. It must be carefully controlled to achieve proper temperature at the interface without excessive material loss while ensuring adequate plasticization for bonding.

21. D — Lap joint

Ultrasonic welding works best with lap joints because it allows direct transfer of vibrational energy from the



Unlock all 505 questions + timed mock exams

→ <https://certs.theorypractice.app/cweng>

\$2.99/week or \$6.99/month · cancel anytime · scan to start

Unofficial study material · not affiliated with any certifying body



sonotrode through one component to the interface. This configuration maximizes the efficiency of energy transfer and provides sufficient surface area for bonding.

22. C — Tunneling defects due to insufficient heat input

Insufficient heat input in friction stir welding can lead to lack of consolidation, where the material doesn't properly plasticize and flow, resulting in tunneling defects or voids along the weld seam. This is a common quality issue that requires proper parameter selection.

23. B — To maintain pressure between components during heating and forging

The axial force in friction welding maintains contact between the components throughout the process, particularly during the forge phase. This pressure ensures plastic deformation of the heated material, expelling oxides and contaminants while creating intimate contact for bonding.

24. A — Ultrasonic welding

Ultrasonic welding is ideal for joining thermoplastics in electronics because it generates localized heating without damaging heat-sensitive components, creates bonds quickly (often in less than a second), doesn't require additional materials, and can join small, delicate parts without thermal damage to surrounding areas.

25. D — Wavelength of the laser beam

CO_2 lasers operate at a wavelength of $10.6 \mu\text{m}$ (infrared spectrum), while Nd:YAG lasers operate at $1.06 \mu\text{m}$. This wavelength difference affects beam delivery methods and absorption characteristics in different materials.

26. C — 10^{-3} to 10^{-6} Torr

Electron beam welding requires a high vacuum (10^{-3} to 10^{-6} Torr) to prevent beam scattering from air molecules and to maintain beam focus over the working distance.

27. B — Electromagnetic lenses

In electron beam welding systems, electromagnetic lenses focus the electron beam much like optical lenses focus light, but using magnetic fields to control the path of the charged electrons.

28. A — Vaporization of the material at high power density

The extremely high power density of laser and electron beams causes rapid vaporization of the material, creating a vapor-filled cavity (keyhole) that allows for deep penetration welding.

29. D — 10^6 W/cm^2 or higher

Keyhole mode welding requires power densities of approximately 10^6 W/cm^2 or higher to vaporize the material and create a vapor-filled cavity that enables deep penetration.

30. C — Aluminum

Aluminum has high reflectivity (approximately 98%) to the $10.6 \mu\text{m}$ wavelength of CO_2 lasers, making it difficult to couple sufficient energy into the material for effective welding.



Unlock all 505 questions + timed mock exams

→ <https://certs.theorypractice.app/cweng>

\$2.99/week or \$6.99/month · cancel anytime · scan to start

Unofficial study material · not affiliated with any certifying body



Ready to pass?

Unlock the full CWENG Test Prep bank, every explanation, and unlimited timed mock exams.

Scan to start practising

<https://certs.theorypractice.app/cweng>

Watch the full video walkthrough on YouTube @CertsQuizPrep



Unlock all 505 questions + timed mock exams

→ <https://certs.theorypractice.app/cweng>

\$2.99/week or \$6.99/month · cancel anytime · scan to start